#### **Features**


- Low-Voltage and Standard-Voltage Operation
  - $-2.7 (V_{CC} = 2.7V \text{ to } 5.5V)$
  - $-1.8 (V_{CC} = 1.8V \text{ to } 5.5V)$
- Low-Power Devices (I<sub>SB</sub> = 6 μA @ 5.5V) Available
- Internally Organized 4096 x 8, 8192 x 8
- 2-Wire Serial Interface
- Schmitt Trigger, Filtered Inputs for Noise Suppression
- Bidirectional Data Transfer Protocol
- 100 kHz (1.8V) and 400 kHz (2.5V) Clock Rate for AT24C32A
- 400 kHz (1.8V) Clock Rate for AT24C64A
- Write Protect Pin for Hardware Data Protection
- 32-Byte Page Write Mode (Partial Page Writes Allowed)
- Self-Timed Write Cycle (5 ms Max)
- · High Reliability
  - Endurance: 1 Million Write Cycles
  - Data Retention: 100 Years
- Automotive Grade, Extended Temperature and Lead-free/Halogen-free Devices Available
- 8-lead JEDEC PDIP, 8-lead JEDEC SOIC, 8-lead EIAJ SOIC, 8-lead MAP and 8-lead TSSOP Packages

## **Description**


The AT24C32A/64A provides 32,768/65,536 bits of serial electrically erasable and programmable read only memory (EEPROM) organized as 4096/8192 words of 8 bits each. The device's cascadable feature allows up to 8 devices to share a common 2-wire bus. The device is optimized for use in many industrial and commercial applications where low power and low voltage operation are essential. The AT24C32A/64A is available in space saving 8-lead JEDEC PDIP, 8-lead JEDEC SOIC, 8-lead EIAJ SOIC, 8-lead MAP and 8-lead TSSOP packages and is accessed via a 2-wire serial interface. In addition, the entire family is available in 2.7V (2.7V to 5.5V) and 1.8V (1.8V to 5.5V) versions.

## **Pin Configurations**

Pin Name	Function
A0 - A2	Address Inputs
SDA	Serial Data
SCL	Serial Clock Input
WP	Write Protect









2-Wire Serial EEPROM 32K (4096 x 8) 64K (8192 x 8)

AT24C32A AT24C64A






## **Absolute Maximum Ratings\***

Operating Temperature55° C to +125° C
Storage Temperature65° C to +150° C
Voltage on Any Pin with Respect to Ground1.0V to +7.0V
Maximum Operating Voltage 6.25V
DC Output Current

\*NOTICE:

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

## **Block Diagram**



## **Pin Description**

**SERIAL CLOCK (SCL):** The SCL input is used to positive edge clock data into each EEPROM device and negative edge clock data out of each device.

**SERIAL DATA (SDA):** The SDA pin is bidirectional for serial data transfer. This pin is open-drain driven and may be wire-ORed with any number of other open-drain or open collector devices.

**DEVICE/ADDRESSES (A2, A1, A0):** The A2, A1 and A0 pins are device address inputs that are hardwired or left not connected for hardware compatibility with other AT24Cxx devices. When the pins are hardwired, as many as eight 32K/64K devices may be addressed on a single bus system (device addressing is discussed in detail under the Device Addressing section). If the pins are left floating, the A2, A1 and A0 pins will be internally pulled down to GND if the capacitive coupling to the circuit board  $V_{CC}$  plane is <3 pF. If coupling is >3 pF, Atmel recommends connecting the address pins to GND.

**WRITE PROTECT (WP):** The write protect input, when connected to GND, allows normal write operations. When WP is connected high to  $V_{CC}$ , all write operations to the memory are inhibited. If the pin is left floating, the WP pin will be internally pulled down to GND if the capacitive coupling to the circuit board  $V_{CC}$  plane is <3 pF. If coupling is >3 pF, Atmel recommends connecting the pin to GND. Switching WP to  $V_{CC}$  prior to a write operation creates a software write protect function.

## **Memory Organization**

AT24C32A/64A, 32K/64K SERIAL EEPROM: The 32K/64K is internally organized as 128/256 pages of 32 bytes each. Random word addressing requires a 12/13-bit data word address.





# Pin Capacitance<sup>(1)</sup>

Applicable over recommended operating range from  $T_A$  = 25° C, f = 1.0 MHz,  $V_{CC}$  = +1.8V.

Symbol Test Condition		Max	Units	Conditions
C <sub>I/O</sub>	Input/Output Capacitance (SDA)	8	pF	$V_{I/O} = 0V$
C <sub>IN</sub>	Input Capacitance (A <sub>0</sub> , A <sub>1</sub> , A <sub>2</sub> , SCL)	6	pF	$V_{IN} = 0V$

Note: 1. This parameter is characterized and is not 100% tested.

### **DC Characteristics**

Applicable over recommended operating range from:  $T_{AI} = -40^{\circ}$  C to  $+85^{\circ}$  C,  $V_{CC} = +1.8$ V to +5.5V,  $T_{AE} = -40^{\circ}$  C to  $+125^{\circ}$  C,  $V_{CC} = +1.8$ V to +5.5V (unless otherwise noted).

Symbol	Parameter	Test Condition		Min	Тур	Max	Units
V <sub>CC1</sub>	Supply Voltage			1.8		5.5	V
$V_{CC2}$	Supply Voltage			2.5		5.5	V
$V_{CC3}$	Supply Voltage			2.7		5.5	V
$V_{CC4}$	Supply Voltage			4.5		5.5	V
I <sub>CC1</sub>	Supply Current	V <sub>CC</sub> = 5.0V	READ at 400 kHz		0.4	1.0	mA
$I_{CC2}$	Supply Current	V <sub>CC</sub> = 5.0V	WRITE at 400 kHz		2.0	3.0	mA
I <sub>SB1</sub>	Standby Current (1.8V option)	V <sub>CC</sub> = 1.8V	$V_{IN} = V_{CC}$ or $V_{SS}$			1.0	μΑ
I <sub>SB2</sub>	Standby Current (2.5V option)	V <sub>CC</sub> = 2.5V	$V_{IN} = V_{CC}$ or $V_{SS}$			2.0	μΑ
I <sub>SB3</sub>	Standby Current (2.7V option)	V <sub>CC</sub> = 2.7V	$V_{IN} = V_{CC}$ or $V_{SS}$			2.0	μΑ
I <sub>SB4</sub>	Standby Current (5V option)	V <sub>CC</sub> = 4.5 - 5.5V	$V_{IN} = V_{CC}$ or $V_{SS}$			6.0	μΑ
ILI	Input Leakage Current	$V_{IN} = V_{CC}$ or $V_{SS}$			0.10	3.0	μΑ
I <sub>LO</sub>	Output Leakage Current	V <sub>OUT</sub> = V <sub>CC</sub> or V <sub>SS</sub>			0.05	3.0	μΑ
V <sub>IL</sub>	Input Low Level <sup>(1)</sup>			-0.6		V <sub>CC</sub> x 0.3	V
V <sub>IH</sub>	Input High Level <sup>(1)</sup>			V <sub>CC</sub> x 0.7		V <sub>CC</sub> + 0.5	V
V <sub>OL2</sub>	Output Low Level	V <sub>CC</sub> = 3.0V	I <sub>OL</sub> = 2.1 mA			0.4	V
V <sub>OL1</sub>	Output Low Level	V <sub>CC</sub> = 1.8V	I <sub>OL</sub> = 0.15 mA			0.2	V

Note: 1.  $V_{IL}$  min and  $V_{IH}$  max are reference only and are not tested.

## **AC Characteristics**

Applicable over recommended operating range from  $T_{AI}$  = -40° C to +85° C,  $T_{AE}$  = -40° C to +125° C,  $V_{CC}$  = +1.8V to +5.5V, CL = 1 TTL Gate and

100 pF (unless otherwise noted).

			AT24	C32A			AT24	C64A		
		1.8V 2.5V – 5.0V		1.8V - 3.6V			5.0V			
Symbol	Parameter	Min	Max	Min	Max	Min	Max	Min	Max	Units
f <sub>SCL</sub>	Clock Frequency, SCL		100		400		400		400	kHz
$t_{LOW}$	Clock Pulse Width Low	4.7		1.3		1.3		1.2		μs
t <sub>HIGH</sub>	Clock Pulse Width High	4.0		0.6		0.6		0.6		μs
t <sub>l</sub>	Noise Suppression Time <sup>(1)</sup>		100		50		100		50	ns
t <sub>AA</sub>	Clock Low to Data Out Valid	0.1	4.5	0.1	0.9	0.2	0.9	0.1	0.9	μs
t <sub>BUF</sub>	Time the bus must be free before a new transmission can start <sup>(2)</sup>	4.7		1.3		1.3		1.2		μs
t <sub>HD.STA</sub>	Start Hold Time	4.0		0.6		0.6		0.6		μs
t <sub>SU.STA</sub>	Start Set-up Time	4.7		0.6		0.6		0.6		μs
t <sub>HD.DAT</sub>	Data In Hold Time	0		0		0		0		μs
t <sub>SU.DAT</sub>	Data In Set-up Time	200		100		100		100		ns
t <sub>R</sub>	Inputs Rise Time <sup>(2)</sup>		1.0		0.3		0.3		0.3	μs
t <sub>F</sub>	Inputs Fall Time <sup>(2)</sup>		300		300		300		300	ns
t <sub>SU.STO</sub>	Stop Set-up Time	4.7		0.6		0.6		0.6		μs
t <sub>DH</sub>	Data Out Hold Time	100		50		200		50		ns
t <sub>WR</sub>	Write Cycle Time		20 or 5 <sup>(3)</sup>		10 or 5 <sup>(3)</sup>		20 or 5 <sup>(3)</sup>		10 or 5 <sup>(3)</sup>	ms
Endurance <sup>(1)</sup>	5.0V, 25° C, Page Mode	1M		1M		1M		1M		Write Cycles

- Notes: 1. This parameter is characterized and is not 100% tested ( $T_A = 25^{\circ} C$ ).
  - 2. This parameter is characterized and is not 100% tested.
  - 3. The Write Cycle Time of 5 ms only applies to the AT24C32A/64A devices bearing the process letter "A" on the package (the mark is located in the lower right corner on the top side of the package).





### **Device Operation**

**CLOCK and DATA TRANSITIONS:** The SDA pin is normally pulled high with an external device. Data on the SDA pin may change only during SCL low time periods (refer to Data Validity timing diagram). Data changes during SCL high periods will indicate a start or stop condition as defined below.

**START CONDITION:** A high-to-low transition of SDA with SCL high is a start condition which must precede any other command (refer to Start and Stop Definition timing diagram).

**STOP CONDITION:** A low-to-high transition of SDA with SCL high is a stop condition. After a read sequence, the stop command will place the EEPROM in a standby power mode (refer to Start and Stop Definition timing diagram).

**ACKNOWLEDGE:** All addresses and data words are serially transmitted to and from the EEPROM in 8-bit words. The EEPROM sends a zero during the ninth clock cycle to acknowledge that it has received each word.


**STANDBY MODE**: The AT24C32A/64A features a low power standby mode which is enabled: a) upon power-up and b) after the receipt of the STOP bit and the completion of any internal operations.

**MEMORY RESET:** After an interruption in protocol, power loss or system reset, any 2-wire part can be reset by following these steps:

(a) Clock up to 9 cycles, (b) look for SDA high in each cycle while SCL is high and then (c) create a start condition as SDA is high.


## **Bus Timing**

SCL: Serial Clock, SDA: Serial Data I/O



## **Write Cycle Timing**


SCL: Serial Clock, SDA: Serial Data I/O




Note: 1. The write cycle time  $t_{WR}$  is the time from a valid stop condition of a write sequence to the end of the internal clear/write cycle.




# **Data Validity**



# **Start and Stop Definition**



# **Output Acknowledge**



## **Device Addressing**

The 32K/64K EEPROM requires an 8-bit device address word following a start condition to enable the chip for a read or write operation (refer to Figure 1). The device address word consists of a mandatory one, zero sequence for the first four most significant bits as shown. This is common to all 2-wire EEPROM devices.

The 32K/64K uses the three device address bits A2, A1, A0 to allow as many as eight devices on the same bus. These bits must compare to their corresponding hardwired input pins. The A2, A1, and A0 pins use an internal proprietary circuit that biases them to a logic low condition if the pins are allowed to float.

The eighth bit of the device address is the read/write operation select bit. A read operation is initiated if this bit is high and a write operation is initiated if this bit is low.

Upon a compare of the device address, the EEPROM will output a zero. If a compare is not made, the device will return to standby state.

**NOISE PROTECTION:** Special internal circuitry placed on the SDA and SCL pins prevent small noise spikes from activating the device.

**DATA SECURITY:** The AT24C32A/64A has a hardware data protection scheme that allows the user to write protect the entire memory when the WP pin is at  $V_{CC}$ .

## Write Operations

BYTE WRITE: A write operation requires two 8-bit data word addresses following the device address word and acknowledgment. Upon receipt of this address, the EEPROM will again respond with a zero and then clock in the first 8-bit data word. Following receipt of the 8-bit data word, the EEPROM will output a zero and the addressing device, such as a microcontroller, must terminate the write sequence with a stop condition. At this time the EEPROM enters an internally-timed write cycle,  $t_{WR}$ , to the nonvolatile memory. All inputs are disabled during this write cycle and the EEPROM will not respond until the write is complete (refer to Figure 2).

**PAGE WRITE:** The 32K/64K EEPROM is capable of 32-byte page writes.

A page write is initiated the same way as a byte write, but the microcontroller does not send a stop condition after the first data word is clocked in. Instead, after the EEPROM acknowledges receipt of the first data word, the microcontroller can transmit up to 31 more data words. The EEPROM will respond with a zero after each data word received. The microcontroller must terminate the page write sequence with a stop condition (refer to Figure 3).

The data word address lower 5 bits are internally incremented following the receipt of each data word. The higher data word address bits are not incremented, retaining the memory page row location. When the word address, internally generated, reaches the page boundary, the following byte is placed at the beginning of the same page. If more than 32 data words are transmitted to the EEPROM, the data word address will "roll over" and previous data will be overwritten.

**ACKNOWLEDGE POLLING:** Once the internally-timed write cycle has started and the EEPROM inputs are disabled, acknowledge polling can be initiated. This involves sending a start condition followed by the device address word. The read/write bit is representative of the operation desired. Only if the internal write cycle has completed will the EEPROM respond with a zero, allowing the read or write sequence to continue.





## **Read Operations**

Read operations are initiated the same way as write operations with the exception that the read/write select bit in the device address word is set to one. There are three read operations: current address read, random address read and sequential read.

**CURRENT ADDRESS READ:** The internal data word address counter maintains the last address accessed during the last read or write operation, incremented by one. This address stays valid between operations as long as the chip power is maintained. The address "roll over" during read is from the last byte of the last memory page, to the first byte of the first page. The address "roll over" during write is from the last byte of the current page to the first byte of the same page.

Once the device address with the read/write select bit set to one is clocked in and acknowledged by the EEPROM, the current address data word is serially clocked out. The microcontroller does not respond with an input zero but does generate a following stop condition (refer to Figure 4).

**RANDOM READ:** A random read requires a "dummy" byte write sequence to load in the data word address. Once the device address word and data word address are clocked in and acknowledged by the EEPROM, the microcontroller must generate another start condition. The microcontroller now initiates a current address read by sending a device address with the read/write select bit high. The EEPROM acknowledges the device address and serially clocks out the data word. The microcontroller does not respond with a zero but does generate a following stop condition (refer to Figure 5).

**SEQUENTIAL READ:** Sequential reads are initiated by either a current address read or a random address read. After the microcontroller receives a data word, it responds with an acknowledge. As long as the EEPROM receives an acknowledge, it will continue to increment the data word address and serially clock out sequential data words. When the memory address limit is reached, the data word address will "roll over" and the sequential read will continue. The sequential read operation is terminated when the microcontroller does not respond with a zero but does generate a following stop condition (refer to Figure 6).

Figure 1. Device Address




Figure 2. Byte Write





Figure 3. Page Write



Notes: 1. \* = DON'T CARE bits

2. † = DON'T CARE bits for the 32K

Figure 4. Current Address Read








Figure 5. Random Read



Note: 1. \* = DON'T CARE bits

Figure 6. Sequential Read



# AT24C32A Ordering Information

Ordering Code	Package	Operation Range
AT24C32A-10PI-2.7	8P3	
AT24C32AN-10SI-2.7	8S1	la directal Tanana anti-una
AT24C32AW-10SI-2.7	8S2	Industrial Temperature (-40° C to 85° C)
AT24C32A-10TI-2.7	8A2	(-40 0 10 03 0)
AT24C32AY1-10YI-2.7	8Y1	
AT24C32A-10PI-1.8	8P3	
AT24C32AN-10SI-1.8	8S1	le direttial Tarana setura
AT24C32AW-10SI-1.8	8S2	Industrial Temperature (-40° C to 85° C)
AT24C32A-10TI-1.8	8A2	(-40 0 10 03 0)
AT24C32AY1-10YI-1.8	8Y1	
AT24C32AN-10SU-2.7	8S1	1 16 /11 6 /
AT24C32AN-10SU-1.8	8S1	Lead-free/Halogen-free/ Industrial Temperature
AT24C32A-10TU-2.7	8A2	(-40° C to 85° C)
AT24C32A-10TU-1.8	8A2	(-40 0 10 03 0)
		Lead-free/Halogen-free/
AT24C32AN-10SQ-2.7	8S1	High Grade/Extended Temperature
		(-40° C to 125° C))
AT24C22AN 400F 2.7	004	High Grade/Extended Temperature
AT24C32AN-10SE-2.7	8S1	(-40° C to 125° C)

Note: For 2.7V devices used in the 4.5V to 5.5V range, please refer to performance values in the AC and DC Characteristics tables.

	Package Type					
8P3	8-lead, 0.300" Wide, Plastic Dual Inline Package (PDIP)					
8S1	8-lead, 0.150" Wide, Plastic Gull Wing Small Outline (JEDEC SOIC)					
8S2	8-lead, 0.209" Body, Plastic Small Outline (EIAJ SOIC)					
8A2	8-lead, 0.170" Wide, Thin Shrink Small Outline Package (TSSOP)					
8Y1	8-lead, 4.90 mm x 3.00 mm Body, Dual Footprint, Non-leaded, Miniature Array Package (MAP)					
	Options					
-2.7	Low Voltage (2.7V to 5.5V)					
-1.8	Low Voltage (1.8V to 5.5V)					





## **AT24C64A Ordering Information**


Ordering Code	Package	Operation Range	
AT24C64A-10PI-2.7	8P3		
AT24C64AN-10SI-2.7	8S1		
AT24C64AW-10SI-2.7	8S2	Industrial Temperature (-40° C to 85° C)	
AT24C64A-10TI-2.7	8A2	(-40 0 10 03 0)	
AT24C64AY1-10YI-2.7	8Y1		
AT24C64A-10PI-1.8	8P3		
AT24C64AN-10SI-1.8	8S1		
AT24C64AW-10SI-1.8	8S2	Industrial Temperature (-40° C to 85° C)	
AT24C64A-10TI-1.8	8A2	(-40 C to 65 C)	
AT24C64AY1-10YI-1.8	8Y1		
AT24C64AN-10SU-2.7	8S1		
AT24C64AN-10SU-1.8	8S1	Lead-free/Halogen-free/ Industrial Temperature	
AT24C64A-10TU-2.7	8A2	(-40° C to 85° C)	
AT24C64A-10TU-1.8	8A2	(-40 C to 65 C)	
		Lead-free/Halogen-free/	
AT24C64AN-10SQ-2.7	8S1	High Grade/Extended Temperature	
		(-40° C to 125° C))	
AT24004AN 400F 2.7	004	High Grade/Extended Temperature	
AT24C64AN-10SE-2.7	8S1	(-40° C to 125° C)	

Note: For 2.7V devices used in the 4.5V to 5.5V range, please refer to performance values in the AC and DC Characteristics tables.


	Package Type				
8P3	8-lead, 0.300" Wide, Plastic Dual Inline Package (PDIP)				
8S1	8-lead, 0.150" Wide, Plastic Gull Wing Small Outline (JEDEC SOIC)				
8S2	8-lead, 0.209" Body, Plastic Small Outline (EIAJ SOIC)				
8A2	8-lead, 0.170" Wide, Thin Shrink Small Outline Package (TSSOP)				
8Y1	8-lead, 4.90 mm x 3.00 mm Body, Dual Footprint, Non-leaded, Miniature Array Package (MAP)				
	Options				
-2.7	Low Voltage (2.7V to 5.5V)				
-1.8	Low Voltage (1.8V to 5.5V)				

## **Package Drawings**


#### **8P3 - PDIP**



Top View



**End View** 



#### **COMMON DIMENSIONS**

(Unit of Measure = inches)

SYMBOL	MIN	NOM	MAX	NOTE
А			0.210	2
A2	0.115	0.130	0.195	
b	0.014	0.018	0.022	5
b2	0.045	0.060	0.070	6
b3	0.030	0.039	0.045	6
С	0.008	0.010	0.014	
D	0.355	0.365	0.400	3
D1	0.005			3
Е	0.300	0.310	0.325	4
E1	0.240	0.250	0.280	3
е	1			
eA		4		
L	0.115	0.130	0.150	2

Notes:

- 1. This drawing is for general information only; refer to JEDEC Drawing MS-001, Variation BA for additional information.
- 2. Dimensions A and L are measured with the package seated in JEDEC seating plane Gauge GS-3.
- 3. D, D1 and E1 dimensions do not include mold Flash or protrusions. Mold Flash or protrusions shall not exceed 0.010 inch.
- 4. E and eA measured with the leads constrained to be perpendicular to datum.
- 5. Pointed or rounded lead tips are preferred to ease insertion.
- 6. b2 and b3 maximum dimensions do not include Dambar protrusions. Dambar protrusions shall not exceed 0.010 (0.25 mm).


01/09/02








### 8S1 - JEDEC SOIC



Top View



Side View

E1 D

**End View** 

# **COMMON DIMENSIONS** (Unit of Measure = mm)

SYMBOL	BOL MIN NOM		MAX	NOTE
А	1.35	_	1.75	
A1	0.10	-	0.25	
b	0.31	_	0.51	
С	0.17	_	0.25	
D	4.80	_	5.00	
E1	3.81	_	3.99	
Е	5.79	_	6.20	
е				
L	0.40	_	1.27	
Ø	0°	_	8°	

Note: These drawings are for general information only. Refer to JEDEC Drawing MS-012, Variation AA for proper dimensions, tolerances, datums, etc.


10/7/03




1150 E. Cheyenne Mtn. Blvd. Colorado Springs, CO 80906 **TITLE 8S1**, 8-lead (0.150" Wide Body), Plastic Gull Wing Small Outline (JEDEC SOIC)


DRAWING NO. 8S1 B

#### 8S2 - EIAJ SOIC





**End View** 



Side View

#### **COMMON DIMENSIONS** (Unit of Measure = mm)


SYMBOL	MIN	NOM	MAX	NOTE
Α	1.70		2.16	
A1	0.05		0.25	
b	0.35		0.48	5
С	0.15		0.35	5
D	5.13		5.35	
E1	5.18		5.40	2, 3
Е	7.70		8.26	
L	0.51		0.85	
Ø	0°		8°	
е		1.27 BSC		4

- Notes: 1. This drawing is for general information only; refer to EIAJ Drawing EDR-7320 for additional information.

  2. Mismatch of the upper and lower dies and resin burrs are not included.

  - 3. It is recommended that upper and lower cavities be equal. If they are different, the larger dimension shall be regarded.
  - 4. Determines the true geometric position.
  - 5. Values b and C apply to pb/Sn solder plated terminal. The standard thickness of the solder layer shall be 0.010 +0.010/-0.005 mm.


10/7/03








#### **8A2 - TSSOP**




Top View





Side View



**End View** 

#### **COMMON DIMENSIONS**

(Unit of Measure = mm)

	`		,	
SYMBOL	MIN	NOM	MAX	NOTE
D	2.90	3.00	3.10	2, 5
Е	6.40 BSC			
E1	4.30	4.40	4.50	3, 5
А	_	_	1.20	
A2	0.80	1.00	1.05	
b	0.19	_	0.30	4
е	0.65 BSC			
L	0.45	0.60	0.75	
L1	1.00 REF			

- Notes: 1. This drawing is for general information only. Refer to JEDEC Drawing MO-153, Variation AA, for proper dimensions, tolerances, datums, etc.
  - 2. Dimension D does not include mold Flash, protrusions or gate burrs. Mold Flash, protrusions and gate burrs shall not exceed 0.15 mm (0.006 in) per side.
  - 3. Dimension E1 does not include inter-lead Flash or protrusions. Inter-lead Flash and protrusions shall not exceed 0.25 mm (0.010 in) per side.
  - 4. Dimension b does not include Dambar protrusion. Allowable Dambar protrusion shall be 0.08 mm total in excess of the b dimension at maximum material condition. Dambar cannot be located on the lower radius of the foot. Minimum space between protrusion and adjacent lead is 0.07 mm.
  - 5. Dimension D and E1 to be determined at Datum Plane H.

5/30/02




2325 Orchard Parkway San Jose, CA 95131

TITLE
8A2, 8-lead, 4.4 mm Body, Plastic
Thin Shrink Small Outline Package (TSSOP)

DRAWING NO.	REV.
8A2	В
1	

#### 8Y1 - MAP





### **Atmel Corporation**

2325 Orchard Parkway San Jose, CA 95131, USA Tel: 1(408) 441-0311

Fax: 1(408) 487-2600

#### Regional Headquarters

#### Europe

Atmel Sarl Route des Arsenaux 41 Case Postale 80 CH-1705 Fribourg Switzerland

Tel: (41) 26-426-5555 Fax: (41) 26-426-5500

#### Asia

Room 1219 Chinachem Golden Plaza 77 Mody Road Tsimshatsui East Kowloon Hong Kong

Tel: (852) 2721-9778 Fax: (852) 2722-1369

#### Japan

9F, Tonetsu Shinkawa Bldg. 1-24-8 Shinkawa Chuo-ku, Tokyo 104-0033 Japan

Tel: (81) 3-3523-3551 Fax: (81) 3-3523-7581

#### **Atmel Operations**

#### Memory

2325 Orchard Parkway San Jose, CA 95131, USA Tel: 1(408) 441-0311 Fax: 1(408) 436-4314

#### Microcontrollers

2325 Orchard Parkway San Jose, CA 95131, USA Tel: 1(408) 441-0311 Fax: 1(408) 436-4314

La Chantrerie BP 70602

44306 Nantes Cedex 3, France Tel: (33) 2-40-18-18

Fax: (33) 2-40-18-19-60

#### ASIC/ASSP/Smart Cards

Zone Industrielle 13106 Rousset Cedex, France Tel: (33) 4-42-53-60-00

Fax: (33) 4-42-53-60-01

1150 East Cheyenne Mtn. Blvd. Colorado Springs, CO 80906, USA

Tel: 1(719) 576-3300 Fax: 1(719) 540-1759

Scottish Enterprise Technology Park Maxwell Building East Kilbride G75 0QR, Scotland

Tel: (44) 1355-803-000 Fax: (44) 1355-242-743

#### RF/Automotive

Theresienstrasse 2 Postfach 3535 74025 Heilbronn, Germany Tel: (49) 71-31-67-0 Fax: (49) 71-31-67-2340

1150 East Cheyenne Mtn. Blvd. Colorado Springs, CO 80906, USA

Tel: 1(719) 576-3300 Fax: 1(719) 540-1759

Biometrics/Imaging/Hi-Rel MPU/ High Speed Converters/RF Datacom

Avenue de Rochepleine

BP 123

38521 Saint-Egreve Cedex, France

Tel: (33) 4-76-58-30-00 Fax: (33) 4-76-58-34-80

Literature Requests www.atmel.com/literature

**Disclaimer:** Atmel Corporation makes no warranty for the use of its products, other than those expressly contained in the Company's standard warranty which is detailed in Atmel's Terms and Conditions located on the Company's web site. The Company assumes no responsibility for any errors which may appear in this document, reserves the right to change devices or specifications detailed herein at any time without notice, and does not make any commitment to update the information contained herein. No licenses to patents or other intellectual property of Atmel are granted by the Company in connection with the sale of Atmel products, expressly or by implication. Atmel's products are not authorized for use as critical components in life support devices or systems.

© Atmel Corporation 2004. All rights reserved. Atmel<sup>®</sup> and combinations thereof, are the registered trademarks of Atmel Corporation or its subsidiaries. Other terms and product names may be the trademarks of others.